

# ARC SERIES (INVERTER)

## Features

- Electrode 1.6-3.15 mm continuous use  
Electrode 4.00 mm -Intermittent use.
- Excellent Arc Strike with inbuilt Arc Force & Hot start.
- Quick & minium maintenance with single PCB design.

MODEL: **RA25**



## Technical Specifications:

|                          |                   |                     |          |
|--------------------------|-------------------|---------------------|----------|
| Products Type            | : ARC 250         | No-load Loss (W)    | : 40     |
| Model                    | : RA25            | Efficiency (%)      | : 85     |
| Input Supply (V)         | : AC 415±15%, 3Ph | Power Factor        | : 0.93   |
| Frequency (HZ)           | : 50/60           | Insulation Grade    | : F      |
| Rated Input Current (A)  | : 13              | Protection Grade    | : IP 21  |
| Power (KVA)              | : 9.4             | Inverter Technology | : MOSFET |
| No-load Voltage (V)      | : 60              | Arc Force Control   | : YES    |
| Output Current Range (A) | : 30-250          | Net Weight (Kg)     | : 17.5   |
| Rated Output Voltage (V) | : 30              | Welding Accessories | : NO     |
| Duty Cycle (%)           | 60                |                     |          |

**Applications** : General Fabrication / Maintenance Works

\* In view of continuous development RALLIWOLF reserves the right to modify / alter the design / modification without prior notice

## Ralli Wolf Industries Ltd.

An ISO 9001 : 2015 certified Organisation

### Corporate Office :

Diamond Heritage, 510, 5th Floor,  
16, Strand Road, Kolkata - 700001 (India)  
E : info@ralliwolf.com, P : +91 81000 80353  
CIN : U51109WB1996PLC077080

### Sales Network :

Ahmedabad, Bangalore, Baroda, Bhopal, Chennai, Coimbatore, Cuttack, Delhi, Gurgaon, Guwahati, Jaipur, Jamshedpur, Kolkata, Ludhiana, Mumbai, Nagpur, Pune, Secunderabad, Siliguri, Thiruvananthapuram, Trichy, Vishakhapatnam

Follow us :



www.ralliwolf.com +91 90734 93011