



## TIG SERIES



## MMA



### • Specifications

Products Type	TIG 200 P
Model	RT20P
Input Voltage (V)	AC 220 ± 15%
Rated Input Current (A)	28.2/43.6
Power (KVA)	6.2 / 9.59
No-load Voltage (V)	56
Output Current (A)	5-200
Rated Output Voltage (V)	28
Duty Cycle (%)	60
No-load Loss (W)	40
Efficiency (%)	80
Power Factor	0.73
Pre-Flow (Sec.)	2
Post-Flow (Sec.)	0-25
Arcing Way	High Frequency
Net Weight (Kg)	13
MMA Function	Available
Inverter Technology	MOSFET

### • Features

- High Frequency ignition
- Superior arc performance
- Post-flow function
- Light and compact, easy to carry and use
- Economises tungsten use with a stable output & high duty cycle

### • Standard Accessories



\* In view of continuous development RALLIWOLF reserves the right to modify / alter the design / modification without prior notice

## Ralli Wolf Industries Ltd.

(Formerly Ralli Engineering Ltd)

An ISO 9001 : 2015 certified Organisation

**Regd. Office :** 4, Fairlie Place Kolkata - 700001 (India), E : info@ralliwolf.com, P : +91 33 2262 7341

SALES NETWORK : Ahmedabad | Akola | Baroda | Bangalore | Bhubaneswar | Bhopal | Chennai | Coimbatore | Cuttack | Delhi  
Faridabad | Guwahati | Indore | Jaipur | Jamshedpur | Kolkata | Ludhiana | Mumbai | Nagpur | Pune | Raipur | Secunderabad | Trichy